

SCHOOL SECURITY SOLUTIONS

PDQ's GT 135 LED Classroom Intruder Cylindrical Lock is designed to allow a staff member to use the inside cylinder to lock the outside of the door, without compromising safety to the occupants in the room. But how does a staff member know if the outside lever is locked? Until now, it required opening the door and checking the lever. PDQ's 135 LED Classroom Intruder function eliminates the need to open the door. Simply press the button on the lock, and...if the Red LED lights up, the outside lever is locked and secure. If the Red LED does not light up, this indicates the outside lever is not locked and secure.



LEVER DESIGNS



BSN — BOSTON



MIA — MIAMI



PHL — PHILADELPHIA

FEATURES

- Complies with California Education Code (Functions GT135, GT135LED, GT145)
- Red LED (Light Emitting Diode) outside lever status indicator.
- Pushing the button located on the rose of the inside lock, Red LED illuminates indicating the outside lever is locked.
- Offered with cylinder housings compatible with Best® Small Format Inter-changeable cores, Schlage® Large Format Interchangeable cores and most others.
- **Large Format Inter-changeable cores only available with PHL lever.**
- Keying options available, compatible with most key systems.
- Battery life rating: 10 years*
- Battery type: CR1220
- Patent Pending

PERFORMANCE, MECHANICAL

- Factory tested to over 2 million cycles (2 times the ANSI/BHMA Grade 1 std)
- Lever torque tested to 2,100 in-lbs (3 times the ANSI/BHMA Grade 1 std)



OUTSIDE LEVER UNLOCKED

TO CHECK THE SECURITY OF THE OUTSIDE LEVER, PRESS THE BUTTON. IF THE RED LED LIGHTS UP, THAT CONFIRMS THE OUTSIDE LEVER IS LOCKED AND SECURE.

SCHOOL SECURITY FUNCTIONS

FUNCTION	FUNCTION NUMBER	INSIDE OUTSIDE	DESCRIPTION
KEYED			
WITH LED STATUS INDICATOR			
Vestibule Class Room Security	GT135LED		<ul style="list-style-type: none"> • Latchbolt operated by lever from either side • Key in either lever locks outside lever • Key in either lever unlocks outside lever • Inside lever always free • Red LED Outside Lever Status Indicator • Lock Directional Arrow • Patent Pending
			F110
WITHOUT LED STATUS INDICATOR			
Vestibule Class Room Security	GT135		<ul style="list-style-type: none"> • Latchbolt operated by lever from either side • Key in either lever locks outside lever • Key in either lever unlocks outside lever • Inside lever always free
			F110
Vestibule Class Room Security	GT145		<ul style="list-style-type: none"> • Latchbolt operated by lever from either side • Key in either lever locks outside lever • Key in either lever unlocks outside lever • Inside lever always free • Lock Directional Arrow™
			F110
NON KEYED			
NEW Time Out Lock	GT173		<ul style="list-style-type: none"> • Latchbolt by lever from either side unless push button on outside is depressed. Lock returns to passage mode upon release of push button. • Inside lever locked only when pushing button on outside lever. • Inside lever unlocked by emergency release of button from outside.
			—

*Battery tested to over 7,300 illumination cycles. 10 year life rating is calculated using 1 sec per illumination @ 2 illuminations per day @ 365 days per year @ 10 years